

TeSys Power

Deca, Giga Motor circuit breakers

Introduction

Circuit breakers for motor protection and control

Deca, Giga motor circuit breakers provide compact, reliable and efficient solutions for:

- isolation,
- protection against short circuits and overloads,
- On-Off manual control of motors from 0.06 to 250 kW.

They are conforming to, depending of the versions, IEC/EN 60947-1, IEC/EN 60947-2, IEC/EN 60947-4-1 and UL 60947-4-1, CSA 22.2 n° 60947-4-1.

Deca, Giga protection technologies

Deca, Giga circuit breakers are carried with 3 variants:

- Magnetic detection: product references GV2LE, GV2L, GV3L, GV4L, GV4LE for protection against short-circuit.
 - Thermal-magnetic: product references GV2ME ⁽¹⁾, GV2P, GV3P, GV4P, GV4PE, GV5, GV6 for protection against short-circuits, overload, phase loss and phase unbalance.
 - Advanced: product references GV4PEM combines GV4P protections and motor jam, long start, ground-fault protections.
- With a magnetic circuit breaker, a thermal relay is frequently associated in order to have a short circuit protection and an overload protection.

TeSys Deca - Frame 2 circuit breakers: 45 mm width, for motors up to 15 kW

The most commonly used circuit breaker. with a choice of about 100 auxiliaries and accessories. TeSys Deca Frame 2 circuit breakers and TeSys K, Deca contactors can be easily assembled as a single block with one accessory.

The high Frame 2 electrical endurance (up to 100 000 operating cycles) makes it very suitable for direct manual motor control, especially ref. GV2ME ⁽¹⁾ (thermal-magnetic c.b., lth up to 32 A).

Enclosure mounting is well adapted to ref. GV2L and GV2P, with their possible extended rotary handle and visible trip indication.

TeSys Deca - Frame 3 circuit breakers: 55 mm width, for motors up to 45 kW

High performance breakers, high breaking capacity (Ics 100 kA/400 V for ratings up to 32 A, 50 kA up to 80 A).

Wide choice of auxiliaries / accessories, possible extended rotary handle. Visible tri indication.

Patented Everlink connectors provide everlasting connection (no re-tightening required).

Direct monoblock starter assembly with TeSys Deca contactors. No accessory required.

TeSys Deca - Frame 4 circuit breakers: 81 mm width, for motors up to 55 kW

State-of-the-art technology, TeSys Deca Frame 4 is compact and robust. Electronic core of ref. GV4P gives a great detection accuracy, with alarming and advanced protections for ref. GV4PEM, GV4PB.

Magnetic, electronic thermal-magnetic, or electronic thermal-magnetic with advanced protections versions.

Ratings up to 115 A with breaking capacity Ics of 25 kA/400 V (B series), 50 kA/400 V (N series) or 100 kA/400 V (S series).

TeSys Giga - Frame 5: 105 mm width, for motors up to 110 kW / Frame 6: 140 mm width, for motors up to 250 kW

TeSys Giga - Frame 5 and 6 with advanced thermal-magnetic trip unit provide more effective protection to high power motors in the most demanding appliances.

They provide protection to motors against overloads with selection of a trip class (5, 10 or 20), short-circuits, phase unbalance or phase loss.

Adjustable over-load and short circuit current settings provide flexibility.

Wide choice of auxiliaries/accessories are available for indication, control and operation.



GV2LE

GV2P

GV2ME



GV3L

GV3P80



GV4E●●●

GV4●●●●



GV5P150F

GV6P500F

⁽¹⁾ Ref. GV2ME●●AP are specific GV2ME references for CEE zone.



Characteristics:
p. B6/72 to B6/76

Curves:
p. B6/83 to B6/85

Dimensions:
p. B6/93 to B6/97

Schemes:
p. B6/99



GV2ME003

Motor
circuit
breakers

Motor circuit breakers from 0.06 to 11 kW / 400 V

Deca - Frame 2 (ref. GV2ME): control by push button, connection by spring terminals

Standard power ratings of 3-phase motors
50/60 Hz in category AC-3/AC-3e

400/415 V 500 V

P Icu Ics ⁽¹⁾ P Icu Ics ⁽¹⁾

kW kA % kW kA %

— — — — — —

0.06 ★ ★ — — —

0.09 ★ ★ — — —

0.12 ★ ★ — — —

0.18 ★ ★ — — —

0.25 ★ ★ 0.37 ★ ★

0.37 ★ ★ 0.37 ★ ★

0.55 ★ ★ 0.55 ★ ★

0.75 ★ ★ 1.1 ★ ★

1.1 ★ ★ 1.5 ★ ★

1.5 ★ ★ 2.2 ★ ★

2.2 ★ ★ 3 50 100

3 ★ ★ 4 10 100

4 ★ ★ 5.5 10 100

5.5 15 50 7.5 6 75

7.5 15 50 9 6 75

9 15 40 11 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

11 15 40 15 4 75

Setting
range
of thermal
trips
⁽²⁾

A

0.1...0.16

0.16...0.25

0.25...0.40

0.40...0.63

0.63...1

1...1.6

1.6...2.5

2.5...4

4...6.3

6...10

10...14

13...18

17...23

20...25

Magnetic
tripping
current
I_n ± 20 %

A

1.93

3.08

5.8

9.3

15.1

26.2

39

74

91

149

253.4

341

341

388.3

Reference

GV2ME013

GV2ME023

GV2ME033

GV2ME043

GV2ME053

GV2ME063

GV2ME073

GV2ME083

GV2ME103

GV2ME143

GV2ME163

GV2ME203

GV2ME213

GV2ME223

Contact blocks

Description	Mounting	Maximum number	Type of contacts	Sold in lots of	Unit reference
Instantaneous auxiliary contacts	Front	1	N/O + N/C	10	GVAE113
			N/O + N/O	10	GVAE203
	LH side	2	N/O + N/C	1	GVAN113
			N/O + N/O	1	GVAN203

(1) Maximum rating which can be mounted in enclosures GV2MC or MP, please consult your Regional Sales Office

(2) The thermal trip setting must be within the range marked on the graduated knob.

★ > 100 kA.